

Parametry techniczne zestawu ZHCN-E:									
Typ:	ZHCN-160 E	ZHCN-250 E	ZHCN-315 E	ZHCN-400 E	ZHCN-500 E	ZHCN-630 E	ZHCN-800 E	ZHCN-1000 E	ZHCN-1200 E
Zakres średnic [mm]:	∅ 50 – ∅ 160	∅ 63 – ∅ 250	∅ 90 – ∅ 315	∅ 160 – ∅ 400	∅ 250 – ∅ 500	∅ 315 – ∅ 630	∅ 500 – ∅ 800	∅ 450 – ∅ 1000	∅ 630 – ∅ 1200
Napięcie [V], częstotliwość prądu[Hz]:	230, 50 +/-15%					400, 50 +/-15%			
Moc [kW]:	2,75	3,65	3,85	4,95	5,1	8,65	10	19,5	22,4
Masa zestawu* [kg]:	92	112	125	192	244	546	698	1625	4093
Wkłady redukcyjne [mm]:	∅ 50, ∅63, ∅75, ∅90, ∅110, ∅125, ∅140	∅63, ∅75, ∅90, ∅110, ∅125, ∅140, ∅160, ∅180, ∅200, ∅225	∅90, ∅110, ∅125, ∅140, ∅160, ∅180, ∅200, ∅225, ∅250, ∅280	∅110, ∅125, ∅140, ∅160, ∅180, ∅200, ∅225, ∅250, ∅280, ∅315, ∅355	∅250, ∅280, ∅315, ∅355, ∅400, ∅450	∅315, ∅355, ∅400, ∅450, ∅500, ∅560	∅500, ∅560, ∅630, ∅710	∅450, ∅500, ∅560, ∅630, ∅710, ∅800, ∅900	∅630, ∅710, ∅800, ∅900
Masa wkładów [kg]:	9	25,5	35	50	59	180	755	1350	1200

*-masa bez wkładów redukcyjnych